arXiv:1604.01570v1 [math.RT] 6 Apr 2016

STRUCTURE CONSTANTS OF PSEUDO H-TYPE ALGEBRAS IN SOME INTEGRAL BASES

K. FURUTANI, I. MARKINA

Abstract. We present the structural constants of low dimensional pseudo H-type algebras.

1. Definition of pseudo H-type algebra

Let $\mathfrak{n}=\mathfrak{z}\oplus\mathfrak{v}$ be a nilpotent graded Lie algebra, $\langle\,.\,,.\,\rangle_{r,s}$ a non-degenerate symmetric bi-linear form on $\mathfrak{z}$ of index (r,s) and $\langle\,.\,,.\,\rangle$ a non-degenerate symmetric bi-linear form on $\mathfrak{v}$ that is of index (l,l) in the case $s>0$ and is of index $(n,0)$ if $s=0$. Define the map $J\colon\,\mathfrak{z}\to\mathrm{End}(\mathfrak{v})$ by

$$\langle\,z,[x,y]\,\rangle_{r,s}=\langle\,J_zx,y\,\rangle,\quad z\in\mathfrak{z},\quad x,y\in\mathfrak{v}\,.$$

Then the map J_z is skew symmetric with respect to the bi-linear form $\langle\,.\,,.\,\rangle$ in the following sense

$$\langle\,J_zx,y\,\rangle+\langle\,x,J_zy\,\rangle=0. \tag{1}$$

Definition 1. *A Lie algebra $\mathfrak{n}=(\mathfrak{n},[\,.\,,.\,],\langle\,.\,,.\,\rangle_{r,s}+\langle\,.\,,.\,\rangle)$ is called a pseudo H-type Lie algebra if*

$$J_z^2+\langle\,z\,,z\,\rangle\,\mathrm{Id}_{\mathfrak{v}}=0\quad\textit{for all}\quad z\in\mathfrak{z}\,.$$

The pseudo H-type Lie algebras are in one to one correspondence with the Clifford $\mathrm{Cl}(\mathfrak{z},\langle\,.\,,.\,\rangle_{r,s})$-module structures on $\mathfrak{v}$ admitting a symmetric bi-linear form $\langle\,.\,,.\,\rangle$, satisfying (1), see [1, 2, 5]. We use the isomorphism of scalar vector spaces $(\mathfrak{z},\langle\,.\,,.\,\rangle_{r,s})\cong\mathbb{R}^{r,s}$, $(\mathfrak{v},\langle\,.\,,.\,\rangle)\cong\mathbb{R}^{l,l}$ or $(\mathfrak{v},\langle\,.\,,.\,\rangle)\cong\mathbb{R}^{n,0}$, and the Clifford algebras $\mathrm{Cl}(\mathfrak{z},\langle\,.\,,.\,\rangle_{r,s})\cong\mathrm{Cl}_{r,s}=\mathrm{Cl}(\mathbb{R}^{r,s})$. We also write $\mathfrak{n}_{r,s}$ for pseudo H-type Lie algebras related to the $\mathrm{Cl}_{r,s}$-module of minimal possible dimension (minimal admissible module).

We denote by $z_1,\dots,z_r,z_{r+1},\dots,z_{r+s}$ an orthonormal basis for $\mathbb{R}^{r,s}$ such that

$$\langle\,z_i,z_i\,\rangle_{r,s}=\begin{cases}1, & \text{if}\quad i=1,\dots,r,\\ -1 & \text{if}\quad i=r+1,\dots,r+s.\end{cases}$$

We choose the initial vector v on each Clifford module $\mathfrak{v}$ such that $\langle\,v,v\,\rangle=1$. More about the construction of the bases for $\mathfrak{n}_{r,s}$ and the isomorphism properties see [1, 3, 4].

2010 *Mathematics Subject Classification.* Primary 17B30, 22E60.

Key words and phrases. Clifford module, nilpotent two step algebra, structure constants, pseudo H-type algebras.

The first author has been partially supported by the Grant-in-aid for Scientific Research (C) No. 23540251, *Japan Society for the Promotion of Science*. The second author has been partially supported by the grants of the Norwegian Research Council #239033/F20.

2. Bases and structure constants for pseudo H-type Lie algebras with $r+s=1$

The pseudo H-type Lie algebras $\mathfrak{n}_{1,0}$ and $\mathfrak{n}_{0,1}$ are isomorphic [1, 4]. The minimal admissible module $\mathfrak{v}$ is 2-dimensional. Let $z_1 \in \mathbb{R}^{1,0}$, $\langle z_1, z_1 \rangle_{1,0} = 1$, $J_{z_1}^2 = -\operatorname{Id}_{\mathfrak{v}}$ and $v \in \mathfrak{v}$ with $\langle v, v \rangle = 1$. Then the integral basis of $\mathfrak{n}_{1,0}$ is

$$z_1, \quad v_1 = v, \quad v_2 = J_{z_1} v.$$

Commutators are given in Table 1

Table 1. Commutation relations for $\mathfrak{n}_{1,0}$ and $\mathfrak{n}_{0,1}$

$[r,c]$	v_1	v_2
v_1	0	z_1
v_2	$-z_1$	0

3. Bases and structure constants for pseudo H-type Lie algebras with $r+s=2$

3.1. **H-type Lie algebra $\mathfrak{n}_{2,0}$.** The minimal admissible module $\mathfrak{v}$ is 4-dimensional. The basis for $\mathbb{R}^{2,0}$ is z_1, z_2 and $J_{z_i}^2 = -\operatorname{Id}_{\mathfrak{v}}$, $i = 1, 2$. The basis for $\mathfrak{v}$ is

$$v_1 = v, \quad v_2 = J_{z_2} J_{z_1} v, \quad v_3 = J_{z_1} v, \quad v_4 = J_{z_2} v.$$

Table 2. Commutation relations for $\mathfrak{n}_{2,0}$ and $\mathfrak{n}_{0,2}$

$[r,c]$	v_1	v_2	v_3	v_4
v_1	0	0	z_1	z_2
v_2	0	0	$-z_2$	z_1
v_3	$-z_1$	z_2	0	0
v_4	$-z_2$	$-z_1$	0	0

3.2. **H-type Lie algebra $\mathfrak{n}_{1,1}$.** The minimal admissible module $\mathfrak{v}$ is 4-dimensional. The basis for $\mathbb{R}^{1,1}$ is z_1, z_2 and $J_{z_1}^2 = -\operatorname{Id}_{\mathfrak{v}}$, $J_{z_2}^2 = \operatorname{Id}_{\mathfrak{v}}$. The basis for $\mathfrak{v}$ is

$$v_1 = v, \quad v_2 = J_{z_1} J_{z_2} v, \quad v_3 = J_{z_1} v, \quad v_4 = J_{z_2} v.$$

Table 3. Commutation relations for $\mathfrak{n}_{1,1}$

$[r,c]$	v_1	v_2	v_3	v_4
v_1	0	0	z_1	z_2
v_2	0	0	z_2	z_1
v_3	$-z_1$	$-z_2$	0	0
v_4	$-z_2$	$-z_1$	0	0

3.3. **H-type Lie algebra $\mathfrak{n}_{0,2}$.** The Lie algebra $\mathfrak{n}_{0,2}$ is isomorphic to the Lie algebra $\mathfrak{n}_{2,0}$ and the structural constants are given in Table 2.

4. Bases and structure constants for pseudo H-type Lie algebras with $r+s=3$

4.1. **H-type Lie algebra $\mathfrak{n}_{3,0}$.** The minimal admissible module $\mathfrak{v}$ is 4-dimensional. Basis of $\mathbb{R}^{3,0}$ is z_1, z_2, z_3 and we choose an initial vector $v \in \mathfrak{v}$, $\langle v, v \rangle = 1$ satisfying $J_{z_1} J_{z_2} J_{z_3} v = v$. Then the basis of $\mathfrak{v}$ is the following

$$v_1 = v, \quad v_2 = J_{z_1} v, \quad v_3 = J_{z_2} v, \quad v_4 = J_{z_3} v.$$

Table 4. Commutation relations for $\mathfrak{n}_{3,0}$

$[r,c]$	v_1	v_2	v_3	v_4
v_1	0	z_1	z_2	z_3
v_2	$-z_1$	0	$-z_3$	z_2
v_3	$-z_2$	z_3	0	$-z_1$
v_4	$-z_3$	$-z_2$	z_1	0

4.2. **H-type Lie algebra $\mathfrak{n}_{2,1}$.** The minimal admissible module $\mathfrak{v}$ is 8-dimensional. Basis of $\mathbb{R}^{2,1}$ is z_1, z_2, z_3 and $J_{z_i}^2 = -\operatorname{Id}_{\mathfrak{v}}$, $i = 1, 2$, $J_{z_3}^2 = \operatorname{Id}_{\mathfrak{v}}$. We choose an initial vector $v \in \mathfrak{v}$ such that $\langle v, J_{z_1} J_{z_2} J_{z_3} v \rangle = 0$ and $\langle v, v \rangle = 1$. Then the basis of $\mathfrak{v}$ is the following

$$\begin{array}{llll} v_1 = v, & v_2 = J_{z_2} J_{z_1} v, & v_3 = J_{z_1} J_{z_3} v, & v_4 = J_{z_2} J_{z_3} v, \\ v_5 = J_{z_1} v, & v_6 = J_{z_2} v, & v_7 = J_{z_3} v, & v_8 = J_{z_1} J_{z_2} J_{z_3} v. \end{array}$$

Table 5. Commutation relations for $\mathfrak{n}_{2,1}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8
v_1	0	0	0	0	z_1	z_2	z_3	0
v_2	0	0	0	0	$-z_2$	z_1	0	$-z_3$
v_3	0	0	0	0	z_3	0	z_1	z_2
v_4	0	0	0	0	0	z_3	z_2	$-z_1$
v_5	$-z_1$	z_2	$-z_3$	0	0	0	0	0
v_6	$-z_2$	$-z_1$	0	$-z_3$	0	0	0	0
v_7	$-z_3$	0	$-z_1$	$-z_2$	0	0	0	0
v_8	0	z_3	$-z_2$	z_1	0	0	0	0

4.3. **H-type Lie algebra $\mathfrak{n}_{1,2}$.** The minimal admissible module $\mathfrak{v}$ is 4-dimensional. Basis of $\mathbb{R}^{1,2}$ is z_1, z_2, z_3 and $J_{z_1}^2 = -\operatorname{Id}_{\mathfrak{v}}$, $J_{z_i}^2 = \operatorname{Id}_{\mathfrak{v}}$, $i = 2, 3$. We choose an initial vector $v \in \mathfrak{v}$, $\langle v, v \rangle = 1$, in order to satisfy $J_{z_1} J_{z_2} J_{z_3} v = v$. Then the basis of $\mathfrak{v}$ is the following

$$v_1 = v, \quad v_2 = J_{z_1} v, \quad v_3 = J_{z_2} v, \quad v_4 = J_{z_3} v.$$

TABLE 6. Commutation relations for $\mathfrak{n}_{1,2}$

$[r,c]$	v_1	v_2	v_3	v_4
v_1	0	z_1	z_2	z_3
v_2	$-z_1$	0	z_3	$-z_2$
v_3	$-z_2$	$-z_3$	0	$-z_1$
v_4	$-z_3$	z_2	z_1	0

4.4. ***H*-type Lie algebra $\mathfrak{n}_{0,3}$.** The minimal admissible module $\mathfrak{v}$ is 8-dimensional. Basis of $\mathbb{R}^{0,3}$ is z_1, z_2, z_3 and $J_{z_i}^2 = \mathrm{Id}_{\mathfrak{v}}$, $i = 1, 2, 3$. We choose an initial vector $v \in \mathfrak{v}$, $\langle\, v, v \,\rangle = 1$, such that $\langle\, v, J_{z_1} J_{z_2} J_{z_3} v \,\rangle = 0$. Then the basis of $\mathfrak{v}$ is the following

$$\begin{aligned} &v_1 = v, && v_2 = J_{z_1} J_{z_2} v, && v_3 = J_{z_1} J_{z_3} v, && v_4 = J_{z_2} J_{z_3} v, \\ &v_5 = J_{z_1} v, && v_6 = J_{z_2} v, && v_7 = J_{z_3} v, && v_8 = J_{z_1} J_{z_2} J_{z_3} v \end{aligned}$$

TABLE 7. Commutation relations for $\mathfrak{n}_{0,3}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8
v_1	0	0	0	0	z_1	z_2	z_3	0
v_2	0	0	0	0	$-z_2$	z_1	0	z_3
v_3	0	0	0	0	$-z_3$	0	z_1	$-z_2$
v_4	0	0	0	0	0	$-z_3$	z_2	z_1
v_5	$-z_1$	z_2	z_3	0	0	0	0	0
v_6	$-z_2$	$-z_1$	0	z_3	0	0	0	0
v_7	$-z_3$	0	$-z_1$	$-z_2$	0	0	0	0
v_8	0	$-z_3$	z_2	$-z_1$	0	0	0	0

5. Bases and structure constants for pseudo *H*-type Lie algebras with $r + s = 4$

5.1. ***H*-type Lie algebra $\mathfrak{n}_{4,0}$.** The minimal admissible module $\mathfrak{v}$ is 8-dimensional. Basis of $\mathbb{R}^{4,0}$ is $z_1, \dots, z_4$ and $J_{z_i}^2 = -\mathrm{Id}_{\mathfrak{v}}$, $i = 1, \dots, 4$. We choose an initial vector $v \in \mathfrak{v}$, $\langle\, v, v \,\rangle = 1$, in order to satisfy $J_{z_1} J_{z_2} J_{z_3} J_{z_4} v = v$. Then the basis of $\mathfrak{v}$ is the following

$$\begin{aligned} &v_1 = v, && v_2 = J_{z_1} J_{z_2} v, && v_3 = J_{z_1} J_{z_3} v, && v_4 = J_{z_1} J_{z_4} v, \\ &v_5 = J_{z_1} v, && v_6 = J_{z_2} v, && v_7 = J_{z_3} v, && v_8 = J_{z_4} v. \end{aligned}$$

5.2. ***H*-type Lie algebra $\mathfrak{n}_{3,1}$.** The minimal admissible module $\mathfrak{v}$ is 8-dimensional. Basis of $\mathbb{R}^{3,1}$ is $z_1, \dots, z_4$ and $J_{z_i}^2 = -\mathrm{Id}_{\mathfrak{v}}$, $i = 1, 2, 3$, $J_{z_4}^2 = \mathrm{Id}_{\mathfrak{v}}$. We choose an initial vector $v \in \mathfrak{v}$, $\langle\, v, v \,\rangle = 1$, such that $J_{z_1} J_{z_2} J_{z_3} v = v$. Then the basis of $\mathfrak{v}$ is the following

$$\begin{aligned} &v_1 = v, && v_2 = J_{z_1} v, && v_3 = J_{z_2} v, && v_4 = J_{z_3} v, \\ &v_5 = J_{z_4} v, && v_6 = J_{z_4} J_{z_1} v, && v_7 = J_{z_4} J_{z_2} v, && v_8 = J_{z_4} J_{z_3} v. \end{aligned}$$

TABLE 8. Commutation relations for $\mathfrak{n}_{4,0}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8
v_1	0	0	0	0	z_1	z_2	z_3	z_4
v_2	0	0	0	0	z_2	$-z_1$	$-z_4$	z_3
v_3	0	0	0	0	z_3	z_4	$-z_1$	$-z_2$
v_4	0	0	0	0	z_4	$-z_3$	z_2	$-z_1$
v_5	$-z_1$	$-z_2$	$-z_3$	$-z_4$	0	0	0	0
v_6	$-z_2$	z_1	$-z_4$	z_3	0	0	0	0
v_7	$-z_3$	z_4	z_1	$-z_2$	0	0	0	0
v_8	$-z_4$	$-z_3$	z_2	z_1	0	0	0	0

TABLE 9. Commutation relations for $\mathfrak{n}_{3,1}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8
v_1	0	z_1	z_2	z_3	z_4	0	0	0
v_2	$-z_1$	0	$-z_3$	z_2	0	z_4	0	0
v_3	$-z_2$	z_3	0	$-z_1$	0	0	z_4	0
v_4	$-z_3$	$-z_2$	z_1	0	0	0	0	z_4
v_5	$-z_4$	0	0	0	0	z_1	z_2	z_3
v_6	0	$-z_4$	0	0	$-z_1$	0	$-z_3$	z_2
v_7	0	0	$-z_4$	0	$-z_2$	z_3	0	$-z_1$
v_8	0	0	0	$-z_4$	$-z_3$	$-z_2$	z_1	0

5.3. **H-type Lie algebra $\mathfrak{n}_{2,2}$.** The minimal admissible module $\mathfrak{v}$ is 8-dimensional. Basis of $\mathbb{R}^{2,2}$ is $z_1,\dots,z_4$ and $J_{z_i}^2 = -\operatorname{Id}_{\mathfrak{v}}$, $i=1,2$, $J_{z_i}^2 = \operatorname{Id}_{\mathfrak{v}}$, $i=3,4$. We choose an initial vector $v\in\mathfrak{v}$, $\langle v,v\rangle = 1$ such that $J_{z_1}J_{z_2}J_{z_3}J_{z_4}v = v$. Then the basis of $\mathfrak{v}$ is the following

$$\begin{aligned} &v_1 = v, && v_2 = J_{z_1}J_{z_2}v, && v_3 = J_{z_1}J_{z_3}v, && v_4 = J_{z_1}J_{z_4}v,\\ &v_5 = J_{z_1}v, && v_6 = J_{z_2}v, && v_7 = J_{z_3}v, && v_8 = J_{z_4}v. \end{aligned}$$

TABLE 10. Commutation relations for $\mathfrak{n}_{2,2}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8
v_1	0	0	0	0	z_1	z_2	z_3	z_4
v_2	0	0	0	0	z_2	$-z_1$	z_4	$-z_3$
v_3	0	0	0	0	z_3	$-z_4$	z_1	$-z_2$
v_4	0	0	0	0	z_4	z_3	z_2	z_1
v_5	$-z_1$	$-z_2$	$-z_3$	$-z_4$	0	0	0	0
v_6	$-z_2$	z_1	z_4	$-z_3$	0	0	0	0
v_7	$-z_3$	$-z_4$	$-z_1$	$-z_2$	0	0	0	0
v_8	$-z_4$	$-z_3$	z_2	$-z_1$	0	0	0	0

5.4. **H-type Lie algebra $\mathfrak{n}_{1,3}$.** the minimal admissible module $\mathfrak{v}$ is 8-dimensional. Basis of $\mathbb{R}^{1,3}$ is $z_1,\dots,z_4$ and $J_{z_1}^2 = -\operatorname{Id}_{\mathfrak{v}}$, $J_{z_i}^2 = \operatorname{Id}_{\mathfrak{v}}$, $i=2,3,4$. We choose an initial

vector $v \in \mathfrak{v}$, $\langle\, v, v \,\rangle = 1$ satisfying $J_{z_1} J_{z_2} J_{z_3} v = v$. Then the basis of $\mathfrak{v}$ is the following

$$\begin{aligned} &v_1 = v, && v_2 = J_{z_1} v, && v_3 = J_{z_2} v, && v_4 = J_{z_3} v, \\ &v_5 = J_{z_4} v, && v_6 = J_{z_4} J_{z_1} v, && v_7 = J_{z_4} J_{z_2} v, && v_8 = J_{z_4} J_{z_3} v. \end{aligned}$$

TABLE 11. Commutation relations for $\mathfrak{n}_{1,3}$

$[r, c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8
v_1	0	z_1	z_2	z_3	z_4	0	0	0
v_2	$-z_1$	0	z_3	$-z_2$	0	z_4	0	0
v_3	$-z_2$	$-z_3$	0	$-z_1$	0	0	$-z_4$	0
v_4	$-z_3$	z_2	z_1	0	0	0	0	$-z_4$
v_5	$-z_4$	0	0	0	0	z_1	z_2	z_3
v_6	0	$-z_4$	0	0	$-z_1$	0	z_3	$-z_2$
v_7	0	0	z_4	0	$-z_2$	$-z_3$	0	$-z_1$
v_8	0	0	0	z_4	$-z_3$	z_2	z_1	0

5.5. ***H*-type Lie algebra $\mathfrak{n}_{0,4}$.** The minimal admissible module $\mathfrak{v}$ is 8-dimensional. Basis of $\mathbb{R}^{0,4}$ is $z_1, \dots, z_4$ and $J_{z_i}^2 = \mathrm{Id}_{\mathfrak{v}}$, $i = 1, \dots, 4$. We choose an initial vector $v \in \mathfrak{v}$, $\langle\, v, v \,\rangle = 1$, such that $J_{z_1} J_{z_2} J_{z_3} J_{z_4} v = v$. Then the basis of $\mathfrak{v}$ is the following

$$\begin{aligned} &v_1 = v, && v_2 = J_{z_2} J_{z_1} v, && v_3 = J_{z_3} J_{z_1} v, && v_4 = J_{z_4} J_{z_1} v, \\ &v_5 = J_{z_1} v, && v_6 = J_{z_2} v, && v_7 = J_{z_3} v, && v_8 = J_{z_4} v. \end{aligned}$$

TABLE 12. Commutation relations for $\mathfrak{n}_{0,4}$

$[r, c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8
v_1	0	0	0	0	z_1	z_2	z_3	z_4
v_2	0	0	0	0	z_2	$-z_1$	$-z_4$	z_3
v_3	0	0	0	0	z_3	z_4	$-z_1$	$-z_2$
v_4	0	0	0	0	z_4	$-z_3$	z_2	$-z_1$
v_5	$-z_1$	$-z_2$	$-z_3$	$-z_4$	0	0	0	0
v_6	$-z_2$	z_1	$-z_4$	z_3	0	0	0	0
v_7	$-z_3$	z_4	z_1	$-z_2$	0	0	0	0
v_8	$-z_4$	$-z_3$	z_2	z_1	0	0	0	0

We see that Lie algebras $\mathfrak{n}_{4,0}$ and $\mathfrak{n}_{0,4}$ are isomorphic.

6. Bases and structure constants for pseudo *H*-type Lie algebras with $r + s = 5$

6.1. ***H*-type Lie algebra $\mathfrak{n}_{5,0}$.** The minimal admissible module $\mathfrak{v}$ is 8-dimensional. Basis of $\mathbb{R}^{5,0}$ is $z_1, \dots, z_5$ and $J_{z_i}^2 = -\mathrm{Id}_{\mathfrak{v}}$, $i = 1, \dots, 5$. We choose an initial vector $v \in \mathfrak{v}$, $\langle\, v, v \,\rangle = 1$ to satisfy

$$P_1 v = J_{z_1} J_{z_2} J_{z_3} J_{z_4} v = v, \quad P_2 v = J_{z_1} J_{z_2} J_{z_5} v = v.$$

Then the basis of $\mathfrak{v}$ is the following

$$\begin{aligned} &v_1 = v, && v_2 = J_{z_5} v, && v_3 = J_{z_1} J_{z_3} v, && v_4 = J_{z_1} J_{z_4} v, \\ &v_5 = J_{z_1} v, && v_6 = J_{z_2} v, && v_7 = J_{z_3} v, && v_8 = J_{z_4} v. \end{aligned}$$

TABLE 13. Commutation relations for $\mathfrak{n}_{5,0}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8
v_1	0	z_5	0	0	z_1	z_2	z_3	z_4
v_2	$-z_5$	0	0	0	$-z_2$	z_1	z_4	$-z_3$
v_3	0	0	0	$-z_5$	z_3	z_4	$-z_1$	$-z_2$
v_4	0	0	z_5	0	z_4	$-z_3$	z_2	$-z_1$
v_5	$-z_1$	z_2	$-z_3$	$-z_4$	0	$-z_5$	0	0
v_6	$-z_2$	$-z_1$	$-z_4$	z_3	z_5	0	0	0
v_7	$-z_3$	$-z_4$	z_1	$-z_2$	0	0	0	z_5
v_8	$-z_4$	z_3	z_2	z_1	0	0	$-z_5$	0

6.2. **H-type Lie algebra $\mathfrak{n}_{4,1}$.** The minimal admissible module $\mathfrak{v}$ is 16-dimensional. Basis of $\mathbb{R}^{4,1}$ is $z_1,\dots,z_5$ and $J_{z_i}^2 = -\operatorname{Id}_{\mathfrak{v}}$, $i=1,\dots,4$, $J_{z_5}^2 = \operatorname{Id}_{\mathfrak{v}}$. We choose an initial vector $v\in\mathfrak{v}$, $\langle v,v\rangle = 1$, satisfying $P_1 v = J_{z_1}J_{z_2}J_{z_3}J_{z_4}v = v$. Then the basis of $\mathfrak{v}$ is the following

$$
\begin{aligned}
&v_1 = v, && v_2 = J_{z_1}J_{z_2}v, && v_3 = J_{z_1}J_{z_3}v, && v_4 = J_{z_1}J_{z_4}v,\\
&v_5 = J_{z_1}v, && v_6 = J_{z_2}v, && v_7 = J_{z_3}v, && v_8 = J_{z_4}v,\\
&v_9 = J_{z_5}v, && v_{10} = J_{z_5}J_{z_1}J_{z_2}v, && v_{11} = J_{z_5}J_{z_1}J_{z_3}v, && v_{12} = J_{z_5}J_{z_1}J_{z_4}v,\\
&v_{13} = J_{z_5}J_{z_1}v, && v_{14} = J_{z_5}J_{z_2}v, && v_{15} = J_{z_5}J_{z_3}v, && v_{16} = J_{z_5}J_{z_4}v.
\end{aligned}
$$

TABLE 14. Commutation relations for $\mathfrak{n}_{4,1}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8	v_9	v_{10}	v_{11}	v_{12}	v_{13}	v_{14}	v_{15}	v_{16}
v_1	0	0	0	0	z_1	z_2	z_3	z_4	z_5	0	0	0	0	0	0	0
v_2	0	0	0	0	z_2	$-z_1$	$-z_4$	z_3	0	z_5	0	0	0	0	0	0
v_3	0	0	0	0	z_3	z_4	$-z_1$	$-z_2$	0	0	z_5	0	0	0	0	0
v_4	0	0	0	0	z_4	$-z_3$	z_2	$-z_1$	0	0	0	z_5	0	0	0	0
v_5	$-z_1$	$-z_2$	$-z_3$	$-z_4$	0	0	0	0	0	0	0	0	z_5	0	0	0
v_6	$-z_2$	z_1	$-z_4$	z_3	0	0	0	0	0	0	0	0	0	z_5	0	0
v_7	$-z_3$	z_4	z_1	$-z_2$	0	0	0	0	0	0	0	0	0	0	z_5	0
v_8	$-z_4$	$-z_3$	z_2	z_1	0	0	0	0	0	0	0	0	0	0	0	z_5
v_9	$-z_5$	0	0	0	0	0	0	0	0	0	0	0	z_1	z_2	z_3	z_4
v_{10}	0	$-z_5$	0	0	0	0	0	0	0	0	0	0	z_2	$-z_1$	$-z_4$	z_3
v_{11}	0	0	$-z_5$	0	0	0	0	0	0	0	0	0	z_3	z_4	$-z_1$	$-z_2$
v_{12}	0	0	0	$-z_5$	0	0	0	0	0	0	0	0	z_4	$-z_3$	z_2	$-z_1$
v_{13}	0	0	0	0	$-z_5$	0	0	0	$-z_1$	$-z_2$	$-z_3$	$-z_4$	0	0	0	0
v_{14}	0	0	0	0	0	$-z_5$	0	0	$-z_2$	z_1	$-z_4$	z_3	0	0	0	0
v_{15}	0	0	0	0	0	0	$-z_5$	0	$-z_3$	z_4	z_1	$-z_2$	0	0	0	0
v_{16}	0	0	0	0	0	0	0	$-z_5$	$-z_4$	$-z_3$	z_2	z_1	0	0	0	0

6.3. **H-type Lie algebra $\mathfrak{n}_{3,2}$.** The minimal admissible module $\mathfrak{v}$ is 8-dimensional. Basis of $\mathbb{R}^{3,2}$ is $z_1,\dots,z_5$ and $J_{z_i}^2 = -\operatorname{Id}_{\mathfrak{v}}$, $i=1,2,3$, $J_{z_i}^2 = \operatorname{Id}_{\mathfrak{v}}$, $i=4,5$. We choose an initial vector $v\in\mathfrak{v}$, $\langle v,v\rangle = 1$, such that

$$P_1 v = J_{z_2}J_{z_3}J_{z_4}J_{z_5}v = v, \quad P_2 v = J_{z_1}J_{z_2}J_{z_3}v = v.$$

Then the basis of $\mathfrak{v}$ is the following

$$
\begin{aligned}
&v_1 = v, && v_2 = J_{z_1}v, && v_3 = J_{z_2}v, && v_4 = J_{z_3}v,\\
&v_5 = J_{z_4}v, && v_6 = J_{z_5}v, && v_7 = J_{z_4}J_{z_2}v, && v_8 = J_{z_4}J_{z_3}v.
\end{aligned}
$$

TABLE 15. Commutation relations for $\mathfrak{n}_{3,2}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8
v_1	0	z_1	z_2	z_3	z_4	z_5	0	0
v_2	$-z_1$	0	$-z_3$	z_2	$-z_5$	z_4	0	0
v_3	$-z_2$	z_3	0	$-z_1$	0	0	z_4	z_5
v_4	$-z_3$	$-z_2$	z_1	0	0	0	$-z_5$	z_4
v_5	$-z_4$	z_5	0	0	0	z_1	z_2	z_3
v_6	$-z_5$	$-z_4$	0	0	$-z_1$	0	$-z_3$	z_2
v_7	0	0	$-z_4$	$-z_5$	$-z_2$	z_3	0	$-z_1$
v_8	0	0	z_5	$-z_4$	$-z_3$	$-z_2$	z_1	0

6.4. ***H*-type Lie algebra $\mathfrak{n}_{2,3}$.** The minimal admissible module $\mathfrak{v}$ is 8-dimensional. Basis of $\mathbb{R}^{2,3}$ is $z_1,\dots,z_5$ and $J_{z_i}^2=-\operatorname{Id}_{\mathfrak{v}}$, $i=1,2$, $J_{z_i}^2=\operatorname{Id}_{\mathfrak{v}}$, $i=3,4,5$. We choose an initial vector $v\in\mathfrak{v}$, $\langle\, v,v\,\rangle=1$, such that

$$P_1v=J_{z_1}J_{z_2}J_{z_3}J_{z_4}v=v,\quad P_2v=J_{z_1}J_{z_4}J_{z_5}v=v.$$

Then the basis of $\mathfrak{v}$ is the following

$$\begin{aligned} &v_1=v, && v_2=J_{z_1}v, && v_3=J_{z_2}v, && v_4=J_{z_3}v,\\ &v_5=J_{z_4}v, && v_6=J_{z_5}v, && v_7=J_{z_4}J_{z_2}v, && v_8=J_{z_4}J_{z_3}v. \end{aligned}$$

TABLE 16. Commutation relations for $\mathfrak{n}_{2,3}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8
v_1	0	z_1	z_2	z_3	z_4	z_5	0	0
v_2	$-z_1$	0	0	0	z_5	$-z_4$	$-z_3$	$-z_2$
v_3	$-z_2$	0	0	z_5	0	$-z_3$	z_4	z_1
v_4	$-z_3$	0	$-z_5$	0	0	$-z_2$	$-z_1$	$-z_4$
v_5	$-z_4$	$-z_5$	0	0	0	$-z_1$	z_2	z_3
v_6	$-z_5$	z_4	z_3	z_2	z_1	0	0	0
v_7	0	z_3	$-z_4$	z_1	$-z_2$	0	0	z_5
v_8	0	z_2	$-z_1$	z_4	$-z_3$	0	$-z_5$	0

6.5. ***H*-type Lie algebra $\mathfrak{n}_{1,4}$.** The minimal admissible module $\mathfrak{v}$ is 8-dimensional. Basis of $\mathbb{R}^{1,4}$ is $z_1,\dots,z_5$ and $J_{z_1}^2=-\operatorname{Id}_{\mathfrak{v}}$, $J_{z_i}^2=\operatorname{Id}_{\mathfrak{v}}$, $i=2,3,4,5$. We choose an initial vector $v\in\mathfrak{v}$, $\langle\, v,v\,\rangle=1$ such that

$$P_1v=J_{z_2}J_{z_3}J_{z_4}J_{z_5}v=v,\quad P_2v=J_{z_1}J_{z_2}J_{z_3}v=v.$$

Then the basis of $\mathfrak{v}$ is the following

$$\begin{aligned} &v_1=v, && v_2=J_{z_1}v, && v_3=J_{z_2}v, && v_4=J_{z_3}v,\\ &v_5=J_{z_4}v, && v_6=J_{z_5}v, && v_7=J_{z_4}J_{z_2}v, && v_8=J_{z_4}J_{z_3}v. \end{aligned}$$

TABLE 17. Commutation relations for $\mathfrak{n}_{1,4}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8
v_1	0	z_1	z_2	z_3	z_4	z_5	0	0
v_2	$-z_1$	0	z_3	$-z_2$	$-z_5$	z_4	0	0
v_3	$-z_2$	$-z_3$	0	$-z_1$	0	0	$-z_4$	z_5
v_4	$-z_3$	z_2	z_1	0	0	0	$-z_5$	$-z_4$
v_5	$-z_4$	z_5	0	0	0	z_1	z_2	z_3
v_6	$-z_5$	$-z_4$	0	0	$-z_1$	0	z_3	$-z_2$
v_7	0	0	z_4	z_5	$-z_2$	$-z_3$	0	$-z_1$
v_8	0	0	$-z_5$	z_4	$-z_3$	z_2	z_1	0

6.6. **H-type Lie algebra $\mathfrak{n}_{0,5}$.** The minimal admissible module $\mathfrak{v}$ is 16-dimensional. Basis of $\mathbb{R}^{0,5}$ is $z_1,\dots,z_5$ and $J_{z_i}^2=\mathrm{Id}_{\mathfrak{v}}$, $i=1,\dots,5$. We choose an initial vector $v\in\mathfrak{v}$, $\langle v,v\rangle=1$ in order to satisfy $P_1v=J_{z_2}J_{z_3}J_{z_4}J_{z_5}v=v$. Then the basis of $\mathfrak{v}$ is the following

$$\begin{array}{llll} v_1=v, & v_2=J_{z_1}J_{z_2}v, & v_3=J_{z_1}J_{z_3}v, & v_4=J_{z_1}J_{z_4}v,\\ v_5=J_{z_1}J_{z_5}v, & v_6=J_{z_2}J_{z_5}v, & v_7=J_{z_3}J_{z_5}v, & v_8=J_{z_4}J_{z_5}v,\\ v_9=J_{z_1}v, & v_{10}=J_{z_2}v, & v_{11}=J_{z_3}v, & v_{12}=J_{z_4}v,\\ v_{13}=J_{z_5}v, & v_{14}=J_{z_1}J_{z_2}J_{z_5}v, & v_{15}=J_{z_1}J_{z_3}J_{z_5}v, & v_{16}=J_{z_1}J_{z_4}J_{z_5}v. \end{array}$$

TABLE 18. Commutation relations for $\mathfrak{n}_{0,5}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8	v_9	v_{10}	v_{11}	v_{12}	v_{13}	v_{14}	v_{15}	v_{16}
v_1	0	0	0	0	0	0	0	0	z_1	z_2	z_3	z_4	z_5	0	0	0
v_2	0	0	0	0	0	0	0	0	$-z_2$	z_1	0	0	0	z_5	z_4	$-z_3$
v_3	0	0	0	0	0	0	0	0	$-z_3$	0	z_1	0	0	$-z_4$	z_5	z_2
v_4	0	0	0	0	0	0	0	0	$-z_4$	0	0	z_1	0	z_3	$-z_2$	z_5
v_5	0	0	0	0	0	0	0	0	$-z_5$	0	0	0	z_1	$-z_2$	$-z_3$	$-z_4$
v_6	0	0	0	0	0	0	0	0	0	$-z_5$	z_4	$-z_3$	z_2	z_1	0	0
v_7	0	0	0	0	0	0	0	0	0	$-z_4$	$-z_5$	z_2	z_3	0	z_1	0
v_8	0	0	0	0	0	0	0	0	0	z_3	$-z_2$	$-z_5$	z_4	0	0	z_1
v_9	$-z_1$	z_2	z_3	z_4	z_5	0	0	0	0	0	0	0	0	0	0	0
v_{10}	$-z_2$	$-z_1$	0	0	0	z_5	z_4	$-z_3$	0	0	0	0	0	0	0	0
v_{11}	$-z_3$	0	$-z_1$	0	0	$-z_4$	z_5	z_2	0	0	0	0	0	0	0	0
v_{12}	$-z_4$	0	0	$-z_1$	0	z_3	$-z_2$	z_5	0	0	0	0	0	0	0	0
v_{13}	$-z_5$	0	0	0	$-z_1$	$-z_2$	$-z_3$	$-z_4$	0	0	0	0	0	0	0	0
v_{14}	0	$-z_5$	z_4	$-z_3$	z_2	$-z_1$	0	0	0	0	0	0	0	0	0	0
v_{15}	0	$-z_4$	$-z_5$	z_2	z_3	0	$-z_1$	0	0	0	0	0	0	0	0	0
v_{16}	0	z_3	$-z_2$	$-z_5$	z_4	0	0	$-z_1$	0	0	0	0	0	0	0	0

7. BASES AND STRUCTURE CONSTANTS FOR PSEUDO H-TYPE LIE ALGEBRAS WITH $r+s=6$

7.1. **H-type Lie algebra $\mathfrak{n}_{6,0}$.** the minimal admissible module $\mathfrak{v}$ is 8-dimensional. Basis of $\mathbb{R}^{6,0}$ is $z_1,\dots,z_6$ and $J_{z_i}^2=-\mathrm{Id}_{\mathfrak{v}}$, $i=1,\dots,6$. We choose an initial vector $v\in\mathfrak{v}$, $\langle v,v\rangle=1$, such that

$$P_1v=J_{z_1}J_{z_2}J_{z_3}J_{z_4}v=v,\quad P_2v=J_{z_1}J_{z_2}J_{z_5}J_{z_6}v=v,\quad P_3v=J_{z_1}J_{z_4}J_{z_5}v=v.$$

Then the basis of $\mathfrak{v}$ is the following

$$\begin{aligned} &v_1 = v, && v_2 = J_{z_1} v, && v_3 = J_{z_2} v, && v_4 = J_{z_3} v, \\ &v_5 = J_{z_4} v, && v_6 = J_{z_5} v, && v_7 = J_{z_6} v, && v_8 = J_{z_1} J_{z_2} v. \end{aligned}$$

Useful relations: $J_{z_1} J_{z_3} J_{z_6} v = v$, $-J_{z_2} J_{z_3} J_{z_5} v = v$, $J_{z_2} J_{z_4} J_{z_6} v = v$.

TABLE 19. Commutation relations for $\mathfrak{n}_{6,0}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8
v_1	0	z_1	z_2	z_3	z_4	z_5	z_6	0
v_2	$-z_1$	0	0	$-z_6$	$-z_5$	z_4	z_3	$-z_2$
v_3	$-z_2$	0	0	z_5	$-z_6$	$-z_3$	z_4	z_1
v_4	$-z_3$	z_6	$-z_5$	0	0	z_2	$-z_1$	z_4
v_5	$-z_4$	z_5	z_6	0	0	$-z_1$	$-z_2$	$-z_3$
v_6	$-z_5$	$-z_4$	z_3	$-z_2$	z_1	0	0	z_6
v_7	$-z_6$	$-z_3$	$-z_4$	z_1	z_2	0	0	$-z_5$
v_8	0	z_2	$-z_1$	$-z_4$	z_3	$-z_6$	z_5	0

7.2. ***H*-type Lie algebra $\mathfrak{n}_{5,1}$.** The minimal admissible module $\mathfrak{v}$ is 16-dimensional. Basis of $\mathbb{R}^{5,1}$ is $z_1, \dots, z_6$ and $J_{z_i}^2 = -\operatorname{Id}_{\mathfrak{v}}$, $i = 1, \dots, 5$, $J_{z_6}^2 = \operatorname{Id}_{\mathfrak{v}}$. We choose an initial vector $v \in \mathfrak{v}$, $\langle v, v \rangle = 1$, satisfying

$$P_1 v = J_{z_1} J_{z_2} J_{z_3} J_{z_4} v = v, \quad P_2 v = J_{z_1} J_{z_2} J_{z_5} v = v.$$

Then the basis of $\mathfrak{v}$ for $\mathfrak{n}_{5,1}$ is the following

$$\begin{aligned} &v_1 = v, && v_2 = J_{z_1} v, && v_3 = J_{z_2} v, && v_4 = J_{z_3} v, \\ &v_5 = J_{z_4} v, && v_6 = J_{z_5} v, && v_7 = J_{z_1} J_{z_3} v, && v_8 = J_{z_1} J_{z_4} v, \\ &v_9 = J_{z_6} v, && v_{10} = J_{z_1} J_{z_6} v, && v_{11} = J_{z_2} J_{z_6} v, && v_{12} = J_{z_3} J_{z_6} v, \\ &v_{13} = J_{z_4} J_{z_6} v, && v_{14} = J_{z_5} J_{z_6} v, && v_{15} = J_{z_1} J_{z_3} J_{z_6} v, && v_{16} = J_{z_1} J_{z_4} J_{z_6} v. \end{aligned}$$

Useful relation: $-J_{z_1} J_{z_2} v = J_{z_5} v$.

TABLE 20. Commutation relations for $\mathfrak{n}_{5,1}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8	v_9	v_{10}	v_{11}	v_{12}	v_{13}	v_{14}	v_{15}	v_{16}
v_1	0	z_1	z_2	z_3	z_4	z_5	0	0	z_6	0	0	0	0	0	0	0
v_2	$-z_1$	0	$-z_5$	0	0	z_2	$-z_3$	$-z_4$	0	$-z_6$	0	0	0	0	0	0
v_3	$-z_2$	z_5	0	0	0	$-z_1$	$-z_4$	z_3	0	0	$-z_6$	0	0	0	0	0
v_4	$-z_3$	0	0	0	z_5	$-z_4$	z_1	$-z_2$	0	0	0	$-z_6$	0	0	0	0
v_5	$-z_4$	0	0	$-z_5$	0	z_3	z_2	z_1	0	0	0	0	$-z_6$	0	0	0
v_6	$-z_5$	$-z_2$	z_1	z_4	$-z_3$	0	0	0	0	0	0	0	0	$-z_6$	0	0
v_7	0	z_3	z_4	$-z_1$	$-z_2$	0	0	$-z_5$	0	0	0	0	0	0	z_6	0
v_8	0	z_4	$-z_3$	z_2	$-z_1$	0	z_5	0	0	0	0	0	0	0	0	z_6
v_9	$-z_6$	0	0	0	0	0	0	0	0	$-z_1$	$-z_2$	$-z_3$	$-z_4$	$-z_5$	0	0
v_{10}	0	z_6	0	0	0	0	0	0	z_1	0	$-z_5$	0	0	z_2	z_3	z_4
v_{11}	0	0	z_6	0	0	0	0	0	z_2	z_5	0	0	0	$-z_1$	z_4	$-z_3$
v_{12}	0	0	0	z_6	0	0	0	0	z_3	0	0	0	z_5	$-z_4$	$-z_1$	z_2
v_{13}	0	0	0		z_6	0	0	0	z_4	0	0	$-z_5$	0	z_3	$-z_2$	$-z_1$
v_{14}	0	0	0	0	0	z_6	0	0	z_5	$-z_2$	z_1	z_4	$-z_3$	0	0	0
v_{15}	0	0	0	0	0	0	$-z_6$	0	0	$-z_3$	$-z_4$	z_1	z_2	0	0	$-z_5$
v_{16}	0	0	0	0	0	0	0	$-z_6$	0	$-z_4$	z_3	$-z_2$	z_1	0	z_5	0

7.3. **H-type Lie algebra $\mathfrak{n}_{4,2}$.** The minimal admissible module $\mathfrak{v}$ is 16-dimensional. Basis of $\mathbb{R}^{4,2}$ is $z_1,\dots,z_6$ and $J_{z_i}^2=-\operatorname{Id}_{\mathfrak{v}}$, $i=1,2,3,4$, $J_{z_i}^2=\operatorname{Id}_{\mathfrak{v}}$, $i=5,6$. We choose an initial vector $v\in\mathfrak{v}$, $\langle v,v\rangle=1$ such that

$$P_1v=J_{z_1}J_{z_2}J_{z_3}J_{z_4}v=v,\quad P_2v=J_{z_1}J_{z_2}J_{z_5}J_{z_6}v=v.$$

Then the basis of $\mathfrak{v}$ is the following

$$\begin{array}{llll} v_1=v, & v_2=J_{z_1}v, & v_3=J_{z_2}v, & v_4=J_{z_3}v,\\ v_5=J_{z_4}v, & v_6=J_{z_1}J_{z_2}v, & v_7=J_{z_1}J_{z_3}v, & v_8=J_{z_1}J_{z_4}v,\\ v_9=J_{z_5}v, & v_{10}=J_{z_6}v, & v_{11}=J_{z_1}J_{z_5}v, & v_{12}=J_{z_1}J_{z_6}v,\\ v_{13}=J_{z_3}J_{z_5}v, & v_{14}=J_{z_3}J_{z_6}v, & v_{15}=J_{z_1}J_{z_3}J_{z_5}v, & v_{16}=J_{z_2}J_{z_3}J_{z_5}v. \end{array}$$

Useful relation: $-J_{z_3}J_{z_4}J_{z_5}J_{z_6}v=v$.

TABLE 21. Commutation relations for $\mathfrak{n}_{4,2}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8	v_9	v_{10}	v_{11}	v_{12}	v_{13}	v_{14}	v_{15}	v_{16}
v_1	0	z_1	z_2	z_3	z_4	0	0	0	z_5	z_6	0	0	0	0	0	0
v_2	$-z_1$	0	0	0	0	$-z_2$	$-z_3$	$-z_4$	0	0	$-z_5$	$-z_6$	0	0	0	0
v_3	$-z_2$	0	0	0	0	z_1	$-z_4$	z_3	0	0	z_6	$-z_5$	0	0	0	0
v_4	$-z_3$	0	0	0	0	z_4	z_1	$-z_2$	0	0	0	0	$-z_5$	$-z_6$	0	0
v_5	$-z_4$	0	0	0	0	$-z_3$	z_2	z_1	0	0	0	0	$-z_6$	z_5	0	0
v_6	0	z_2	$-z_1$	$-z_4$	z_3	0	0	0	z_6	$-z_5$	0	0	0	0	0	0
v_7	0	z_3	z_4	$-z_1$	$-z_2$	0	0	0	0	0	0	0	0	0	z_5	z_6
v_8	0	z_4	$-z_3$	z_2	$-z_1$	0	0	0	0	0	0	0	0	0	z_6	$-z_5$
v_9	$-z_5$	0	0	0	0	$-z_6$	0	0	0	0	$-z_1$	$-z_2$	$-z_3$	z_4	0	0
v_{10}	$-z_6$	0	0	0	0	z_5	0	0	0	0	z_2	$-z_1$	$-z_4$	$-z_3$	0	0
v_{11}	0	z_5	$-z_6$	0	0	0	0	0	z_1	$-z_2$	0	0	0	0	z_3	$-z_4$
v_{12}	0	z_6	z_5	0	0	0	0	0	z_2	z_1	0	0	0	0	z_4	z_3
v_{13}	0	0	0	z_5	z_6	0	0	0	z_3	z_4	0	0	0	0	$-z_1$	$-z_2$
v_{14}	0	0	0	z_6	$-z_5$	0	0	0	$-z_4$	z_3	0	0	0	0	z_2	$-z_1$
v_{15}	0	0	0	0	0	0	$-z_5$	$-z_6$	0	0	$-z_3$	$-z_4$	z_1	$-z_2$	0	0
v_{16}	0	0	0	0	0	0	$-z_6$	z_5	0	0	z_4	$-z_3$	z_2	z_1	0	0

7.4. **H-type Lie algebra $\mathfrak{n}_{3,3}$.** The minimal admissible module $\mathfrak{v}$ is 8-dimensional. Basis of $\mathbb{R}^{3,3}$ is $z_1,\dots,z_6$ and $J_{z_i}^2=-\operatorname{Id}_{\mathfrak{v}}$, $i=1,2,3$, $J_{z_i}^2=\operatorname{Id}_{\mathfrak{v}}$, $i=4,5,6$. We choose an initial vector $v\in\mathfrak{v}$, $\langle v,v\rangle=1$, satisfying

$$P_1v=J_{z_1}J_{z_2}J_{z_4}J_{z_5}v=v,\quad P_2v=J_{z_2}J_{z_3}J_{z_5}J_{z_6}v=v,\quad P_3v=J_{z_1}J_{z_2}J_{z_3}v=v$$

Then the basis of $\mathfrak{v}$ is the following

$$\begin{array}{llll} v_1=v, & v_2=J_{z_1}v, & v_3=J_{z_2}v, & v_4=J_{z_3}v\\ v_5=J_{z_4}v, & v_6=J_{z_5}v, & v_7=J_{z_6}v, & v_8=J_{z_1}J_{z_4}v. \end{array}$$

Useful relations:

$$-J_{z_1}J_{z_5}J_{z_6}v=v,\quad -J_{z_3}J_{z_4}J_{z_5}v=v,\quad -J_{z_2}J_{z_4}J_{z_6}v=v,\quad -J_{z_1}J_{z_3}J_{z_4}J_{z_6}v=v.$$

TABLE 22. Commutation relations for $\mathfrak{n}_{3,3}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8
v_1	0	z_1	z_2	z_3	z_4	z_5	z_6	0
v_2	$-z_1$	0	$-z_3$	z_2	0	$-z_6$	z_5	$-z_4$
v_3	$-z_2$	z_3	0	$-z_1$	$-z_6$	0	z_4	z_5
v_4	$-z_3$	$-z_2$	z_1	0	$-z_5$	z_4	0	$-z_6$
v_5	$-z_4$	0	z_6	z_5	0	z_3	z_2	$-z_1$
v_6	$-z_5$	z_6	0	$-z_4$	$-z_3$	0	z_1	z_2
v_7	$-z_6$	$-z_5$	$-z_4$	0	$-z_2$	$-z_1$	0	$-z_3$
v_8	0	z_4	$-z_5$	z_6	z_1	$-z_2$	z_3	0

7.5. ***H*-type Lie algebra $\mathfrak{n}_{2,4}$.** The minimal admissible module $\mathfrak{v}$ is 8-dimensional. Basis of $\mathbb{R}^{2,4}$ is $z_1,\dots,z_6$ and $J_{z_i}^2=-\operatorname{Id}_{\mathfrak{v}}$, $i=1,2$, $J_{z_i}^2=\operatorname{Id}_{\mathfrak{v}}$, $i=3,4,5,6$. We choose an initial vector $v\in\mathfrak{v}$, $\langle\, v,v\,\rangle=1$, such that

$$P_1v=J_{z_1}J_{z_2}J_{z_3}J_{z_4}v=v,\quad P_2v=J_{z_1}J_{z_2}J_{z_5}J_{z_6}v=v,\quad P_3v=J_{z_1}J_{z_3}J_{z_5}v=v.$$

Then the basis of $\mathfrak{v}$ for $\mathfrak{n}_{2,4}$ is the following

$$\begin{aligned} &v_1=v, && v_2=J_{z_1}v, && v_3=J_{z_2}v, && v_4=J_{z_1}J_{z_2}v,\\ &v_5=J_{z_3}v, && v_6=J_{z_4}v, && v_7=J_{z_5}v, && v_8=J_{z_6}v. \end{aligned}$$

Useful relations $-J_{z_2}J_{z_4}J_{z_5}v=v$, $-J_{z_1}J_{z_4}J_{z_6}v=v$, $-J_{z_2}J_{z_3}J_{z_6}v=v$.

TABLE 23. Commutation relations for $\mathfrak{n}_{2,4}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8
v_1	0	z_1	z_2	0	z_3	z_4	z_5	z_6
v_2	$-z_1$	0	0	$-z_2$	z_5	$-z_6$	$-z_3$	z_4
v_3	$-z_2$	0	0	z_1	$-z_6$	$-z_5$	z_4	z_3
v_4	0	z_2	$-z_1$	0	z_4	$-z_3$	z_6	$-z_5$
v_5	$-z_3$	$-z_5$	z_6	$-z_4$	0	0	$-z_1$	z_2
v_6	$-z_4$	z_6	z_5	z_3	0	0	z_2	z_1
v_7	$-z_5$	z_3	$-z_4$	$-z_6$	z_1	$-z_2$	0	0
v_8	$-z_6$	$-z_4$	$-z_3$	z_5	$-z_2$	$-z_1$	0	0

7.6. ***H*-type Lie algebra $\mathfrak{n}_{1,5}$.** The minimal admissible module $\mathfrak{v}$ is 16-dimensional. Basis of $\mathbb{R}^{1,5}$ is $z_1,\dots,z_6$ and $J_{z_1}^2=-\operatorname{Id}_{\mathfrak{v}}$, $J_{z_i}^2=\operatorname{Id}_{\mathfrak{v}}$, $i=2,\dots,6$. We choose an initial vector $v\in\mathfrak{v}$, $\langle\, v,v\,\rangle=1$ satisfying

$$P_1v=J_{z_2}J_{z_3}J_{z_4}J_{z_5}v=v,\quad P_2v=J_{z_1}J_{z_2}J_{z_3}v=v.$$

Then the basis of $\mathfrak{v}$ is the following

$$\begin{aligned} &v_1=v, && v_2=J_{z_1}v, && v_3=J_{z_2}J_{z_6}v, && v_4=J_{z_3}J_{z_6}v,\\ &v_5=J_{z_4}J_{z_6}v, && v_6=J_{z_5}J_{z_6}v, && v_7=J_{z_2}J_{z_4}v, && v_8=J_{z_2}J_{z_5}v,\\ &v_9=J_{z_6}v, && v_{10}=J_{z_1}J_{z_6}v, && v_{11}=J_{z_2}v, && v_{12}=J_{z_3}v,\\ &v_{13}=J_{z_4}v, && v_{14}=J_{z_5}v, && v_{15}=J_{z_2}J_{z_4}J_{z_6}v, && v_{16}=J_{z_2}J_{z_5}J_{z_6}v. \end{aligned}$$

Useful relation: $-J_{z_1}J_{z_4}J_{z_5}v=v$.

TABLE 24. Commutation relations for $\mathfrak{n}_{1,5}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8	v_9	v_{10}	v_{11}	v_{12}	v_{13}	v_{14}	v_{15}	v_{16}
v_1	0	z_1	0	0	0	0	0	0	z_6	0	z_2	z_3	z_4	z_5	0	0
v_2	$-z_1$	0	0	0	0	0	0	0	0	$-z_6$	z_3	$-z_2$	$-z_5$	z_4	0	0
v_3	0	0	0	$-z_1$	0	0	0	0	z_2	$-z_3$	$-z_6$	0	0	0	$-z_4$	$-z_5$
v_4	0	0	z_1	0	0	0	0	0	z_3	z_2	0	$-z_6$	0	0	$-z_5$	z_4
v_5	0	0	0	0	0	z_1	0	0	z_4	z_5	0	0	$-z_6$	0	z_2	$-z_3$
v_6	0	0	0	0	$-z_1$	0	0	0	z_5	$-z_4$	0	0	0	$-z_6$	z_3	z_2
v_7	0	0	0	0	0	0	0	z_1	0	0	$-z_4$	$-z_5$	z_2	z_3	z_6	0
v_8	0	0	0	0	0	0	$-z_1$	0	0	0	$-z_5$	z_4	$-z_3$	z_2	0	z_6
v_9	$-z_6$	0	$-z_2$	$-z_3$	$-z_4$	$-z_5$	0	0	0	$-z_1$	0	0	0	0	0	0
v_{10}	0	z_6	z_3	$-z_2$	$-z_5$	z_4	0	0	z_1	0	0	0	0	0	0	0
v_{11}	$-z_2$	$-z_3$	z_6	0	0	0	z_4	z_5	0	0	0	$-z_1$	0	0	0	0
v_{12}	$-z_3$	z_2	0	z_6	0	0	z_5	$-z_4$	0	0	z_1	0	0	0	0	0
v_{13}	$-z_4$	z_5	0	0	z_6	0	$-z_2$	z_3	0	0	0	0	0	z_1	0	0
v_{14}	$-z_5$	$-z_4$	0	0	0	z_6	$-z_3$	$-z_2$	0	0	0	0	$-z_1$	0	0	0
v_{15}	0	0	z_4	z_5	$-z_2$	$-z_3$	$-z_6$	0	0	0	0	0	0	0	0	z_1
v_{16}	0	0	z_5	$-z_4$	z_3	$-z_2$	0	$-z_6$	0	0	0	0	0	0	$-z_1$	0

7.7. **H-type Lie algebra $\mathfrak{n}_{0,6}$.** The minimal admissible module $\mathfrak{v}$ is 16-dimensional. Basis of $\mathbb{R}^{0,6}$ is $z_1,\dots,z_6$ and $J_{z_i}^2=\mathrm{Id}_{\mathfrak{v}}$, $i=1,\dots,6$. We choose an initial vector $v\in\mathfrak{v}$, $\langle\, v,v\,\rangle=1$ satisfying

$$P_1v=J_{z_1}J_{z_2}J_{z_3}J_{z_4}v=v,\quad P_2v=J_{z_1}J_{z_2}J_{z_5}J_{z_6}v.$$

Then the basis of $\mathfrak{v}$ is the following

$$\begin{array}{llll} v_1=v, & v_2=J_{z_1}J_{z_2}v, & v_3=J_{z_1}J_{z_3}v, & v_4=J_{z_1}J_{z_4}v,\\ v_5=J_{z_1}J_{z_5}v, & v_6=J_{z_1}J_{z_6}v, & v_7=J_{z_3}J_{z_5}v, & v_8=J_{z_3}J_{z_6}v,\\ v_9=J_{z_1}v, & v_{10}=J_{z_2}v, & v_{11}=J_{z_3}v, & v_{12}=J_{z_4}v,\\ v_{13}=J_{z_5}v, & v_{14}=J_{z_6}v, & v_{15}=J_{z_1}J_{z_3}J_{z_5}v, & v_{16}=J_{z_1}J_{z_3}J_{z_6}v. \end{array}$$

Useful relation: $-J_{z_3}J_{z_4}J_{z_5}J_{z_6}v=v$.

TABLE 25. Commutation relations for $\mathfrak{n}_{0,6}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8	v_9	v_{10}	v_{11}	v_{12}	v_{13}	v_{14}	v_{15}	v_{16}
v_1	0	0	0	0	0	0	0	0	z_1	z_2	z_3	z_4	z_5	z_6	0	0
v_2	0	0	0	0	0	0	0	0	$-z_2$	z_1	z_4	$-z_3$	z_6	$-z_5$	0	0
v_3	0	0	0	0	0	0	0	0	$-z_3$	$-z_4$	z_1	z_2	0	0	z_5	z_6
v_4	0	0	0	0	0	0	0	0	$-z_4$	z_3	$-z_2$	z_1	0	0	$-z_6$	z_5
v_5	0	0	0	0	0	0	0	0	$-z_5$	$-z_6$	0	0	z_1	z_2	$-z_3$	$-z_4$
v_6	0	0	0	0	0	0	0	0	$-z_6$	z_5	0	0	$-z_2$	z_1	z_4	$-z_3$
v_7	0	0	0	0	0	0	0	0	0	0	$-z_5$	z_6	z_3	$-z_4$	z_1	$-z_2$
v_8	0	0	0	0	0	0	0	0	0	0	$-z_6$	$-z_5$	z_4	z_3	z_2	z_1
v_9	$-z_1$	z_2	z_3	z_4	z_5	z_6	0	0	0	0	0	0	0	0	0	0
v_{10}	$-z_2$	$-z_1$	z_4	$-z_3$	z_6	$-z_5$	0	0	0	0	0	0	0	0	0	0
v_{11}	$-z_3$	$-z_4$	$-z_1$	z_2	0	0	z_5	z_6	0	0	0	0	0	0	0	0
v_{12}	$-z_4$	z_3	$-z_2$	$-z_1$	0	0	$-z_6$	z_5	0	0	0	0	0	0	0	0
v_{13}	$-z_5$	$-z_6$	0	0	$-z_1$	z_2	$-z_3$	$-z_4$	0	0	0	0	0	0	0	0
v_{14}	$-z_6$	z_5	0	0	$-z_2$	$-z_1$	z_4	$-z_3$	0	0	0	0	0	0	0	0
v_{15}	0	0	$-z_5$	z_6	z_3	$-z_4$	$-z_1$	$-z_2$	0	0	0	0	0	0	0	0
v_{16}	0	0	$-z_6$	$-z_5$	z_4	z_3	z_2	$-z_1$	0	0	0	0	0	0	0	0

8. Bases and structure constants for pseudo H-type Lie algebras with $r+s=7$

8.1. **H-type Lie algebra $\mathfrak{n}_{7,0}$.** The minimal admissible module $\mathfrak{v}$ is 8-dimensional. Basis of $\mathbb{R}^{7,0}$ is $z_1,\dots,z_7$ and $J_{z_i}^2=-\operatorname{Id}_{\mathfrak{v}}$, $i=1,\dots,7$. We choose an initial vector $v\in\mathfrak{v}$, $\langle\, v,v\,\rangle=1$, such that

$$\begin{aligned} P_1v&=J_{z_1}J_{z_2}J_{z_3}J_{z_4}v=v, & P_2v&=J_{z_1}J_{z_2}J_{z_5}J_{z_6}v=v,\\ P_3v&=J_{z_1}J_{z_3}J_{z_5}J_{z_7}v=v, & P_4v&=J_{z_5}J_{z_6}J_{z_7}v=v. \end{aligned}$$

The basis of $\mathfrak{v}$ is the following

$$\begin{aligned} v_1&=v, & v_2&=J_{z_1}v, & v_3&=J_{z_2}v, & v_4&=J_{z_3}v,\\ v_5&=J_{z_4}v, & v_6&=J_{z_5}v, & v_7&=J_{z_6}v, & v_8&=J_{z_7}v,. \end{aligned}$$

Useful relations:

$$P_2P_4v=-J_{z_1}J_{z_2}J_{z_7}v=v,\quad P_3P_4v=J_{z_1}J_{z_3}J_{z_6}v=v,\quad P_1P_2P_3P_4v=J_{z_1}J_{z_4}J_{z_5}v=v,$$

$$P_2P_3P_4v=-J_{z_2}J_{z_3}J_{z_5}v=v,\quad P_1P_3P_4v=J_{z_2}J_{z_4}J_{z_6}v=v,\quad P_1P_2P_4v=J_{z_3}J_{z_4}J_{z_7}v=v.$$

Table 26. Commutation relations for $\mathfrak{n}_{7,0}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8
v_1	0	z_1	z_2	z_3	z_4	z_5	z_6	z_7
v_2	$-z_1$	0	z_7	$-z_6$	$-z_5$	z_4	z_3	$-z_2$
v_3	$-z_2$	$-z_7$	0	z_5	$-z_6$	$-z_3$	z_4	z_1
v_4	$-z_3$	z_6	$-z_5$	0	$-z_7$	z_2	$-z_1$	z_4
v_5	$-z_4$	z_5	z_6	z_7	0	$-z_1$	$-z_2$	$-z_3$
v_6	$-z_5$	$-z_4$	z_3	$-z_2$	z_1	0	$-z_7$	z_6
v_7	$-z_6$	$-z_3$	$-z_4$	z_1	z_2	z_7	0	$-z_5$
v_8	$-z_7$	z_2	$-z_1$	$-z_4$	z_3	$-z_6$	z_5	0

8.2. **H-type Lie algebra $\mathfrak{n}_{3,4}$.** The minimal admissible module $\mathfrak{v}$ is 8-dimensional. Basis of $\mathbb{R}^{3,4}$ is $z_1,\dots,z_7$ with $J_{z_i}^2=-\operatorname{Id}_{\mathfrak{v}}$, $i=1,\dots,3$ and $J_{z_i}^2=\operatorname{Id}_{\mathfrak{v}}$, $i=4,\dots,7$. We choose an initial vector $v\in\mathfrak{v}$, $\langle\, v,v\,\rangle=1$, such that

$$\begin{aligned} P_1v&=J_{z_1}J_{z_2}J_{z_4}J_{z_5}v=v, & P_2v&=J_{z_1}J_{z_2}J_{z_6}J_{z_7}v=v,\\ P_3v&=J_{z_1}J_{z_3}J_{z_5}J_{z_7}v=v, & P_4v&=J_{z_1}J_{z_2}J_{z_3}v=v. \end{aligned}$$

The basis of $\mathfrak{v}$ is the following

$$\begin{aligned} v_1&=v, & v_2&=J_{z_1}v, & v_3&=J_{z_2}v, & v_4&=J_{z_3}v,\\ v_5&=J_{z_4}v, & v_6&=J_{z_5}v, & v_7&=J_{z_6}v, & v_8&=J_{z_7}v,. \end{aligned}$$

Useful relations:

$$P_1P_3P_4v=-J_{z_1}J_{z_4}J_{z_7}v=v,\quad P_2P_3P_4v=-J_{z_1}J_{z_5}J_{z_6}v=v,\quad P_1P_2P_3P_4v=-J_{z_2}J_{z_4}J_{z_6}v=v,$$

$$P_3P_4v=J_{z_2}J_{z_5}J_{z_7}v=v,\quad P_1P_4v=-J_{z_3}J_{z_4}J_{z_5}v=v,\quad P_2P_4v=-J_{z_3}J_{z_6}J_{z_7}v=v.$$

TABLE 27. Commutation relations for $\mathfrak{n}_{3,4}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8
v_1	0	z_1	z_2	z_3	z_4	z_5	z_6	z_7
v_2	$-z_1$	0	$-z_3$	z_2	$-z_7$	$-z_6$	z_5	z_4
v_3	$-z_2$	z_3	0	$-z_1$	$-z_6$	z_7	z_4	$-z_5$
v_4	$-z_3$	$-z_2$	z_1	0	$-z_5$	z_4	$-z_7$	z_6
v_5	$-z_4$	z_7	z_6	z_5	0	z_3	z_2	z_1
v_6	$-z_5$	z_6	$-z_7$	$-z_4$	$-z_3$	0	z_1	$-z_2$
v_7	$-z_6$	$-z_5$	$-z_4$	z_7	$-z_2$	$-z_1$	0	z_3
v_8	$-z_7$	$-z_4$	z_5	$-z_6$	$-z_1$	z_2	$-z_3$	0

8.3. **H-type Lie algebra $\mathfrak{n}_{0,7}$.** The minimal admissible module $\mathfrak{v}$ is 16-dimensional. Basis of $\mathbb{R}^{0,7}$ is $z_1,\dots,z_7$ with $J_{z_i}^2 = \mathrm{Id}_{\mathfrak{v}}$, $i=1,\dots,7$. A result from [4, Theorem11] states that the pseudo H-type Lie algebra $\mathfrak{n}_{0,7}$ is isomorphic to the pseudo H-type Lie algebra $\mathfrak{n}_{7,0}(\mathfrak{v}^+\oplus\mathfrak{v}^-)$ which minimal admissible module is the direct sum of two minimal admissible modules for $\mathfrak{n}_{7,0}$. Here $\mathfrak{v}^+$ and $\mathfrak{v}^-$ are two non-equivalent irreducible modules of the Clifford algebra $\mathrm{Cl}_{7,0}$. The direct sum $\mathfrak{v}^+\oplus\mathfrak{v}^-$ is orthogonal and therefore the table of structural constants will have block diagonal form. To calculate the first block we consider four mutually commuting involutions action on In the first block we

Let $z_1,\dots,z_7,$ are positive orthonormal generators of $C\ell_{7,0}$ and let mutually commuting positive involutions P_i be as above for the admissible module $V^+_{min}\cong\mathbb{R}^{8,0}$ of $C\ell_{7,0}$, that is

$$P_1 = J_{Z_1}J_{Z_2}J_{Z_3}J_{Z_4},\ P_2 = J_{Z_1}J_{Z_2}J_{Z_5}J_{Z_6},$$
$$P_3 = J_{Z_1}J_{Z_3}J_{Z_5}J_{Z_7},\ P_4 = J_{Z_5}J_{Z_6}J_{Z_7},$$

and for the admissible module V^-_{min}

$$Q_1 = \tilde{J}_{Z_1}\tilde{J}_{Z_2}\tilde{J}_{Z_3}\tilde{J}_{Z_4},\ Q_2 = \tilde{J}_{Z_1}\tilde{J}_{Z_2}\tilde{J}_{Z_5}\tilde{J}_{Z_6},$$
$$Q_3 = \tilde{J}_{Z_1}\tilde{J}_{Z_3}\tilde{J}_{Z_5}\tilde{J}_{Z_7},\ Q_4 = \tilde{J}_{Z_5}\tilde{J}_{Z_6}\tilde{J}_{Z_7}.$$

For the admissible module V^+_{min} of $C\ell_{7,0}$ we fix a vector $v\in V^+_{min}$ with the properties that

$$P_i(v) = v, i=1,2,3,4 \text{ and } <v,v>_{8,0}=1$$

and for another admissible module $V^-_{min}\cong\mathbb{R}^{8,0}$ of $C\ell_{7,0}$ we take a vector $w\in V^-_{min}$ with the properties that

$$P_i(w) = w, i=1,2,3\ textand\ P_4(w) = -w, \text{ and } <w,w>_{8,0}=1.$$

We choose positive orthonormal basis $\{X_i\}_{i=0}^{15}$ of $V^+_{min}\oplus V^-_{min}$ with

$$X_0 = v, X_1 = J_{z_1}(v), X_2 = J_{z_2}(v), X_3 = J_{z_3}(v), X_4 = J_{z_4}(v),$$
$$X_5 = J_{z_5}(v), X_6 = J_{z_6}(v), X_7 = J_{z_7}(v),$$
$$X_8 = w, X_9 = \tilde{J}_{z_1}(w), X_{10} = \tilde{J}_{z_2}(w), X_{11} = \tilde{J}_{z_3}(w), X_{12} = \tilde{J}_{z_4}(w),$$
$$X_{13} = \tilde{J}_{z_5}(w), X_{14} = \tilde{J}_{z_6}(w), X_{15} = \tilde{J}_{z_7}(w).$$

Then it holds always $[X_i, X_{8+j}] = 0$ for $i,j = 0,7$.

9. Bases and structure constants for pseudo H-type Lie algebras with $r+s=8$

9.1. **H-type Lie algebra $\mathfrak{n}_{8,0}$.** The minimal admissible module $\mathfrak{v}$ is 16-dimensional. Basis of $\mathbb{R}^{8,0}$ is $z_1,\dots,z_8$ and $J_{z_i}^2=-\operatorname{Id}_{\mathfrak{v}}$, $i=1,\dots,8$. We choose an initial vector $v\in\mathfrak{v}$, $\langle\, v,v\,\rangle=1$, such that

$$P_1v=J_{z_1}J_{z_2}J_{z_3}J_{z_4}v=v,\qquad P_2v=J_{z_1}J_{z_2}J_{z_5}J_{z_6}v=v,$$
$$P_3v=J_{z_2}J_{z_3}J_{z_5}J_{z_7}v=v,\qquad P_4v=J_{z_1}J_{z_2}J_{z_7}J_{z_8}v=v.$$

The basis of $\mathfrak{v}$ is the following

$$\begin{aligned}
&v_1=v, && v_2=J_{z_1}J_{z_2}v, && v_3=J_{z_1}J_{z_3}v, && v_4=J_{z_1}J_{z_4}v,\\
&v_5=J_{z_1}J_{z_5}v, && v_6=J_{z_1}J_{z_6}v, && v_7=J_{z_1}J_{z_7}v, && v_8=J_{z_1}J_{z_8}v,\\
&v_9=J_{z_1}v, && v_{10}=J_{z_2}v, && v_{11}=J_{z_3}v, && v_{12}=J_{z_4}v,\\
&v_{13}=J_{z_5}v, && v_{14}=J_{z_6}v, && v_{15}=J_{z_7}v, && v_{16}=J_{z_8}v.
\end{aligned}$$

Useful relations:

$$P_3P_4v=-J_{z_1}J_{z_3}J_{z_5}J_{z_8}v=v,\quad P_2P_3v=-J_{z_1}J_{z_3}J_{z_6}J_{z_7}v=v,$$
$$P_1P_3v=-J_{z_1}J_{z_4}J_{z_5}J_{z_7}v=v,\quad P_1P_2P_3P_4v=J_{z_1}J_{z_4}J_{z_6}J_{z_8}v=v.$$

The pseudo H-type algebras $\mathfrak{n}_{8,0}$ and $\mathfrak{n}_{8,0}$ are isomorphic

Table 28. Commutation relations for $\mathfrak{n}_{8,0}$ and $\mathfrak{n}_{0,8}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8	v_9	v_{10}	v_{11}	v_{12}	v_{13}	v_{14}	v_{15}	v_{16}
v_1	0	0	0	0	0	0	0	0	z_1	z_2	z_3	z_4	z_5	z_6	z_7	z_8
v_2	0	0	0	0	0	0	0	0	z_2	$-z_1$	$-z_4$	z_3	$-z_6$	z_5	$-z_8$	z_7
v_3	0	0	0	0	0	0	0	0	z_3	z_4	$-z_1$	$-z_2$	z_8	z_7	$-z_6$	$-z_5$
v_4	0	0	0	0	0	0	0	0	z_4	$-z_3$	z_2	$-z_1$	z_7	$-z_8$	$-z_5$	z_6
v_5	0	0	0	0	0	0	0	0	z_5	z_6	$-z_8$	$-z_7$	$-z_1$	$-z_2$	z_4	z_3
v_6	0	0	0	0	0	0	0	0	z_6	$-z_5$	$-z_7$	z_8	z_2	$-z_1$	z_3	$-z_4$
v_7	0	0	0	0	0	0	0	0	z_7	z_8	z_6	z_5	$-z_4$	$-z_3$	$-z_1$	$-z_2$
v_8	0	0	0	0	0	0	0	0	z_8	$-z_7$	z_5	$-z_6$	$-z_3$	z_4	z_2	$-z_1$
v_9	$-z_1$	$-z_2$	$-z_3$	$-z_4$	$-z_5$	$-z_6$	$-z_7$	$-z_8$	0	0	0	0	0	0	0	0
v_{10}	$-z_2$	z_1	$-z_4$	z_3	$-z_6$	z_5	$-z_8$	z_7	0	0	0	0	0	0	0	0
v_{11}	$-z_3$	z_4	z_1	$-z_2$	z_8	z_7	$-z_6$	$-z_5$	0	0	0	0	0	0	0	0
v_{12}	$-z_4$	$-z_3$	z_2	z_1	z_7	$-z_8$	$-z_5$	z_6	0	0	0	0	0	0	0	0
v_{13}	$-z_5$	z_6	$-z_8$	$-z_7$	z_1	$-z_2$	z_4	z_3	0	0	0	0	0	0	0	0
v_{14}	$-z_6$	$-z_5$	$-z_7$	z_8	z_2	z_1	z_3	$-z_4$	0	0	0	0	0	0	0	0
v_{15}	$-z_7$	z_8	z_6	z_5	$-z_4$	$-z_3$	z_1	$-z_2$	0	0	0	0	0	0	0	0
v_{16}	$-z_8$	$-z_7$	z_5	$-z_6$	$-z_3$	z_4	z_2	z_1	0	0	0	0	0	0	0	0

9.2. **H-type Lie algebra $\mathfrak{n}_{7,1}$.** The minimal admissible module $\mathfrak{v}$ is 16-dimensional. Basis of $\mathbb{R}^{7,1}$ is $z_1,\dots,z_8$ with $J_{z_i}^2=-\operatorname{Id}_{\mathfrak{v}}$, $i=1,\dots,7$ and $J_{z_8}^2=\operatorname{Id}_{\mathfrak{v}}$. We choose an initial vector $v\in\mathfrak{v}$, $\langle\, v,v\,\rangle=1$, such that

$$P_1v=J_{z_1}J_{z_2}J_{z_3}J_{z_4}v=v,\qquad P_2v=J_{z_1}J_{z_2}J_{z_5}J_{z_6}v=v,$$
$$P_3v=J_{z_1}J_{z_3}J_{z_5}J_{z_7}v=v,\qquad P_4v=J_{z_5}J_{z_6}J_{z_7}=v.$$

The basis of $\mathfrak{v}$ is the following

$$\begin{aligned}
&v_1=v, && v_2=J_{z_1}v, && v_3=J_{z_2}v, && v_4=J_{z_3}v,\\
&v_5=J_{z_4}v, && v_6=J_{z_5}v, && v_7=J_{z_6}v, && v_8=J_{z_7}v,\\
&v_9=J_{z_8}v, && v_{10}=J_{z_8}J_{z_1}v, && v_{11}=J_{z_8}J_{z_2}v, && v_{12}=J_{z_8}J_{z_3}v,\\
&v_{13}=J_{z_8}J_{z_4}v, && v_{14}=J_{z_8}J_{z_5}v, && v_{15}=J_{z_8}J_{z_6}v, && v_{16}=J_{z_8}J_{z_7}v.
\end{aligned}$$

Useful relations:

$$P_2P_4v = -J_{z_1}J_{z_2}J_{z_7}v = v, \quad P_3P_4v = J_{z_1}J_{z_3}J_{z_6}v = v, \quad P_1P_2P_3P_4v = J_{z_1}J_{z_4}J_{z_5}v = v,$$

$$P_2P_3P_4v = -J_{z_2}J_{z_3}J_{z_5}v = v, \quad P_1P_3P_4v = J_{z_2}J_{z_4}J_{z_6}v = v, \quad P_1P_2P_4v = J_{z_3}J_{z_4}J_{z_7}v = v.$$

TABLE 29. Commutation relations for $\mathfrak{n}_{7,1}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8	v_9	v_{10}	v_{11}	v_{12}	v_{13}	v_{14}	v_{15}	v_{16}
v_1	0	z_1	z_2	z_3	z_4	z_5	z_6	z_7	z_8	0	0	0	0	0	0	0
v_2	$-z_1$	0	z_7	$-z_6$	$-z_5$	z_4	z_3	$-z_2$	0	z_8	0	0	0	0	0	0
v_3	$-z_2$	$-z_7$	0	z_5	$-z_6$	$-z_3$	z_4	z_1	0	0	z_8	0	0	0	0	0
v_4	$-z_3$	z_6	$-z_5$	0	$-z_7$	z_2	$-z_1$	z_4	0	0	0	z_8	0	0	0	0
v_5	$-z_4$	z_5	z_6	z_7	0	$-z_1$	$-z_2$	$-z_3$	0	0	0	0	z_8	0	0	0
v_6	$-z_5$	$-z_4$	z_3	$-z_2$	z_1	0	$-z_7$	z_6	0	0	0	0	0	z_8	0	0
v_7	$-z_6$	z_3	$-z_4$	z_1	z_2	z_7	0	$-z_5$	0	0	0	0	0	0	z_8	0
v_8	$-z_7$	z_2	$-z_1$	$-z_4$	z_3	$-z_6$	z_5	0	0	0	0	0	0	0	0	z_8
v_9	$-z_8$	0	0	0	0	0	0	0	0	z_1	z_2	z_3	z_4	z_5	z_6	z_7
v_{10}	0	$-z_8$	0	0	0	0	0	0	$-z_1$	0	z_7	$-z_6$	$-z_5$	z_4	z_3	$-z_2$
v_{11}	0	0	$-z_8$	0	0	0	0	0	$-z_2$	$-z_7$	0	z_5	$-z_6$	$-z_3$	z_4	z_1
v_{12}	0	0	0	$-z_8$	0	0	0	0	$-z_3$	z_6	$-z_5$	0	$-z_7$	z_2	$-z_1$	z_4
v_{13}	0	0	0	0	$-z_8$	0	0	0	$-z_4$	z_5	z_6	z_7	0	$-z_1$	$-z_2$	$-z_3$
v_{14}	0	0	0	0	0	$-z_8$	0	0	$-z_5$	$-z_4$	z_3	$-z_2$	z_1	0	$-z_7$	z_6
v_{15}	0	0	0	0	0	0	$-z_8$	0	$-z_6$	$-z_3$	$-z_4$	z_1	z_2	z_7	0	$-z_5$
v_{16}	0	0	0	0	0	0	0	$-z_8$	$-z_7$	z_2	$-z_1$	$-z_4$	z_3	$-z_6$	z_5	0

9.3. **H-type Lie algebra $\mathfrak{n}_{4,4}$.** The minimal admissible module is 16-dimensional. Basis of $\mathbb{R}^{4,4}$ is $z_1, \dots, z_8$ and $J_{z_i}^2 = -\operatorname{Id}_{\mathfrak{v}}$, $i = 1,2,3,4$, $J_{z_i}^2 = \operatorname{Id}_{\mathfrak{v}}$, $i = 5,6,7,8$. We choose an initial vector $v \in \mathfrak{v}$, $\langle v, v \rangle = 1$, such that

$$P_1v = J_{z_1}J_{z_2}J_{z_3}J_{z_4}v = v, \qquad P_2v = J_{z_1}J_{z_2}J_{z_5}J_{z_6}v = v,$$
$$P_3v = J_{z_2}J_{z_3}J_{z_5}J_{z_7}v = v, \qquad P_4v = J_{z_1}J_{z_2}J_{z_7}J_{z_8}v = v.$$

Then the basis of $\mathfrak{v}$ is the following

$$v_1 = v, \qquad v_2 = J_{z_1}J_{z_2}v, \qquad v_3 = J_{z_1}J_{z_3}v, \qquad v_4 = J_{z_1}J_{z_4}v,$$
$$v_5 = J_{z_1}J_{z_5}v, \qquad v_6 = J_{z_1}J_{z_6}v, \qquad v_7 = J_{z_1}J_{z_7}v, \qquad v_8 = J_{z_1}J_{z_8}v,$$
$$v_9 = J_{z_1}v, \qquad v_{10} = J_{z_2}v, \qquad v_{11} = J_{z_3}v, \qquad v_{12} = J_{z_4}v,$$
$$v_{13} = J_{z_5}v, \qquad v_{14} = J_{z_6}v, \qquad v_{15} = J_{z_7}v, \qquad v_{16} = J_{z_8}v.$$

Useful relations:

$$P_3P_4v = J_{z_1}J_{z_3}J_{z_5}J_{z_8}v = v, \quad P_2P_3v = J_{z_1}J_{z_3}J_{z_6}J_{z_7}v = v,$$

$$P_1P_3v = -J_{z_1}J_{z_4}J_{z_5}J_{z_7}v = v, \; P_1P_3P_3P_4v = J_{z_1}J_{z_4}J_{z_6}J_{z_8}v = v.$$

9.4. **H-type Lie algebra $\mathfrak{n}_{3,5}$.** The minimal admissible module $\mathfrak{v}$ is 16-dimensional. Basis of $\mathbb{R}^{3,5}$ is $z_1, \dots, z_7$ with $J_{z_i}^2 = -\operatorname{Id}_{\mathfrak{v}}$, $i = 1, \dots, 3$ and $J_{z_i}^2 = \operatorname{Id}_{\mathfrak{v}}$, $i = 4, \dots, 8$. We choose an initial vector $v \in \mathfrak{v}$, $\langle v, v \rangle = 1$, such that

$$P_1v = J_{z_1}J_{z_2}J_{z_4}J_{z_5}v = v, \qquad P_2v = J_{z_1}J_{z_2}J_{z_6}J_{z_7}v = v,$$

$$P_3v = J_{z_1}J_{z_3}J_{z_5}J_{z_7}v = v, \qquad P_4v = J_{z_1}J_{z_2}J_{z_3}v = v.$$

TABLE 30. Commutation relations for $\mathfrak{n}_{4,4}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8	v_9	v_{10}	v_{11}	v_{12}	v_{13}	v_{14}	v_{15}	v_{16}
v_1	0	0	0	0	0	0	0	0	z_1	z_2	z_3	z_4	z_5	z_6	z_7	z_8
v_2	0	0	0	0	0	0	0	0	z_2	$-z_1$	$-z_4$	z_3	z_6	$-z_5$	z_8	$-z_7$
v_3	0	0	0	0	0	0	0	0	z_3	z_4	$-z_1$	$-z_2$	z_8	z_7	$-z_6$	$-z_5$
v_4	0	0	0	0	0	0	0	0	z_4	$-z_3$	z_2	$-z_1$	$-z_7$	z_8	z_5	$-z_6$
v_5	0	0	0	0	0	0	0	0	z_5	$-z_6$	$-z_8$	z_7	z_1	$-z_2$	z_4	$-z_3$
v_6	0	0	0	0	0	0	0	0	z_6	z_5	$-z_7$	$-z_8$	z_2	z_1	$-z_3$	$-z_4$
v_7	0	0	0	0	0	0	0	0	z_7	$-z_8$	z_6	$-z_5$	$-z_4$	z_3	z_1	$-z_2$
v_8	0	0	0	0	0	0	0	0	z_8	z_7	z_5	z_6	z_3	z_4	z_2	z_1
v_9	$-z_1$	$-z_2$	$-z_3$	$-z_4$	$-z_5$	$-z_6$	$-z_7$	$-z_8$	0	0	0	0	0	0	0	0
v_{10}	$-z_2$	z_1	$-z_4$	z_3	z_6	$-z_5$	z_8	$-z_7$	0	0	0	0	0	0	0	0
v_{11}	$-z_3$	z_4	z_1	$-z_2$	z_8	z_7	$-z_6$	$-z_5$	0	0	0	0	0	0	0	0
v_{12}	$-z_4$	$-z_3$	z_2	z_1	$-z_7$	z_8	z_5	$-z_6$	0	0	0	0	0	0	0	0
v_{13}	$-z_5$	$-z_6$	$-z_8$	z_7	$-z_1$	$-z_2$	z_4	$-z_3$	0	0	0	0	0	0	0	0
v_{14}	$-z_6$	z_5	$-z_7$	$-z_8$	z_2	$-z_1$	$-z_3$	$-z_4$	0	0	0	0	0	0	0	0
v_{15}	$-z_7$	$-z_8$	z_6	$-z_5$	$-z_4$	z_3	$-z_1$	$-z_2$	0	0	0	0	0	0	0	0
v_{16}	$-z_8$	z_7	z_5	z_6	z_3	z_4	z_2	$-z_1$	0	0	0	0	0	0	0	0

The basis for $\mathfrak{v}$ is the following

$$
\begin{aligned}
&v_1 = v, && v_2 = J_{z_1} v, && v_3 = J_{z_2} v, && v_4 = J_{z_3} v,\\
&v_5 = J_{z_4} v, && v_6 = J_{z_5} v, && v_7 = J_{z_6} v, && v_8 = J_{z_7} v,\\
&v_9 = J_{z_8} v, && v_{10} = J_{z_8} J_{z_1} v, && v_{11} = J_{z_8} J_{z_2} v, && v_{12} = J_{z_8} J_{z_3} v,\\
&v_{13} = J_{z_8} J_{z_4} v, && v_{14} = J_{z_8} J_{z_5} v, && v_{15} = J_{z_8} J_{z_6} v, && v_{16} = J_{z_8} J_{z_7} v.
\end{aligned}
$$

Useful relations: $P_3P_4v = J_{z_2}J_{z_5}J_{z_7}v = v$, $P_1P_4v = -J_{z_3}J_{z_4}J_{z_5}v = v$,

$$
\begin{aligned}
P_2P_4v = -J_{z_3}J_{z_6}J_{z_7}v = v, \quad P_1P_3P_4v = -J_{z_1}J_{z_4}J_{z_7}v = v,\\
P_2P_3P_4v = -J_{z_1}J_{z_5}J_{z_6}v = v, \quad P_1P_2P_3P_4v = -J_{z_2}J_{z_4}J_{z_6}v = v.
\end{aligned}
$$

TABLE 31. Commutation relations for $\mathfrak{n}_{3,5}$

$[r,c]$	v_1	v_2	v_3	v_4	v_5	v_6	v_7	v_8	v_9	v_{10}	v_{11}	v_{12}	v_{13}	v_{14}	v_{15}	v_{16}
v_1	0	z_1	z_2	z_3	z_4	z_5	z_6	z_7	z_8	0	0	0	0	0	0	0
v_2	$-z_1$	0	$-z_3$	z_2	$-z_7$	$-z_6$	z_5	z_4	0	z_8	0	0	0	0	0	0
v_3	$-z_2$	z_3	0	$-z_1$	$-z_6$	z_7	z_4	$-z_5$	0	0	z_8	0	0	0	0	0
v_4	$-z_3$	$-z_2$	z_1	0	$-z_5$	z_4	$-z_7$	z_6	0	0	0	z_8	0	0	0	0
v_5	$-z_4$	z_7	z_6	z_5	0	z_3	z_2	z_1	0	0	0	0	$-z_8$	0	0	0
v_6	$-z_5$	z_6	$-z_7$	$-z_4$	$-z_3$	0	z_1	$-z_2$	0	0	0	0	0	$-z_8$	0	0
v_7	$-z_6$	$-z_5$	$-z_4$	z_7	$-z_2$	$-z_1$	0	z_3	0	0	0	0	0	0	$-z_8$	0
v_8	$-z_7$	$-z_4$	z_5	$-z_6$	$-z_1$	z_2	$-z_3$	0	0	0	0	0	0	0	0	$-z_8$
v_9	$-z_8$	0	0	0	0	0	0	0	0	z_1	z_2	z_3	z_4	z_5	z_6	z_7
v_{10}	0	$-z_8$	0	0	0	0	0	0	$-z_1$	0	$-z_3$	z_2	$-z_7$	$-z_6$	z_5	z_4
v_{11}	0	0	$-z_8$	0	0	0	0	0	$-z_2$	z_3	0	$-z_1$	$-z_6$	z_7	z_4	$-z_5$
v_{12}	0	0	0	$-z_8$	0	0	0	0	$-z_3$	$-z_2$	z_1	0	$-z_5$	z_4	$-z_7$	z_6
v_{13}	0	0	0	0	z_8	0	0	0	$-z_4$	z_7	z_6	z_5	0	z_3	z_2	z_1
v_{14}	0	0	0	0	0	z_8	0	0	$-z_5$	z_6	$-z_7$	$-z_4$	$-z_3$	0	z_1	$-z_2$
v_{15}	0	0	0	0	0	0	z_8	0	$-z_6$	$-z_5$	$-z_4$	z_7	$-z_2$	$-z_1$	0	z_3
v_{16}	0	0	0	0	0	0	0	z_8	$-z_7$	$-z_4$	z_5	$-z_6$	$-z_1$	z_2	z_3	0

10. TABLE OF CLIFFORD ALGEBRAS

By the red colour we denote the Clifford algebras having minimal admissible module as a double of its irreducible.

TABLE 32. Clifford algebras

9	⋮	⋮	⋮	⋮	⋮	⋮	⋮	⋮	⋮	...
8	$\mathbb{R}(16)$	$\mathbb{C}(16)$	$\mathbb{H}(16)$	$\mathbb{H}^2(16)$	$\mathbb{H}(32)$	$\mathbb{C}(64)$	$\mathbb{R}(128)$	$\mathbb{R}^2(128)$	$\mathbb{R}(256)$	...
7	$\mathbb{C}(8)$	$\mathbb{H}(8)$	$\mathbb{H}^2(8)$	$\mathbb{H}(16)$	$\mathbb{C}(32)$	$\mathbb{R}(64)$	$\mathbb{R}^2(64)$	$\mathbb{R}(128)$	$\mathbb{C}(128)$	...
6	$\mathbb{H}(4)$	$\mathbb{H}^2(4)$	$\mathbb{H}(8)$	$\mathbb{C}(16)$	$\mathbb{R}(32)$	$\mathbb{R}^2(32)$	$\mathbb{R}(64)$	$\mathbb{C}(64)$	$\mathbb{H}(64)$	...
5	$\mathbb{H}^2(2)$	$\mathbb{H}(4)$	$\mathbb{C}(8)$	$\mathbb{R}(16)$	$\mathbb{R}^2(16)$	$\mathbb{R}(32)$	$\mathbb{C}(32)$	$\mathbb{H}(32)$	$\mathbb{H}^2(32)$	...
4	$\mathbb{H}(2)$	$\mathbb{C}(4)$	$\mathbb{R}(8)$	$\mathbb{R}^2(8)$	$\mathbb{R}(16)$	$\mathbb{C}(16)$	$\mathbb{H}(16)$	$\mathbb{H}^2(16)$	$\mathbb{H}(32)$	...
3	$\mathbb{C}(2)$	$\mathbb{R}(4)$	$\mathbb{R}^2(4)$	$\mathbb{R}(8)$	$\mathbb{C}(8)$	$\mathbb{H}(8)$	$\mathbb{H}^2(8)$	$\mathbb{H}(16)$	$\mathbb{C}(32)$	...
2	$\mathbb{R}(2)$	$\mathbb{R}^2(2)$	$\mathbb{R}(4)$	$\mathbb{C}(4)$	$\mathbb{H}(4)$	$\mathbb{H}^2(4)$	$\mathbb{H}(8)$	$\mathbb{C}(16)$	$\mathbb{R}(32)$	...
1	$\mathbb{R}^2$	$\mathbb{R}(2)$	$\mathbb{C}(2)$	$\mathbb{H}(2)$	$\mathbb{H}^2(2)$	$\mathbb{H}(4)$	$\mathbb{C}(8)$	$\mathbb{R}(16)$	$\mathbb{R}^2(16)$	...
0	$\mathbb{R}$	$\mathbb{C}$	$\mathbb{H}$	$\mathbb{H}^2$	$\mathbb{H}(2)$	$\mathbb{C}(4)$	$\mathbb{R}(8)$	$\mathbb{R}(8)$	$\mathbb{R}(16)$	...
s/r	0	1	2	3	4	5	6	7	8	...

REFERENCES

[1] C. Autenried, K. Furutani, I. Markina, *Pseudo-metric 2-step nilpotent Lie algebras*, arXiv 1410.3244.

[2] P. Ciatti, *Scalar products on Clifford modules and pseudo-H-type Lie algebras*. Ann. Mat. Pura Appl. **178** (2000), no. 4, p. 1–32.

[3] K. Furutani, I. Markina, *Existence of the lattice on general H-type groups*. J. Lie Theory, 24, (2014), 979-1011. arXiv: 1305.6814

[4] K. Furutani and I. Markina, *Complete classification of H-type algebras: I*. arXiv:1512.03469.

[5] M. Godoy Molina, A. Korolko, I. Markina, *Sub-semi-Riemannian geometry of general H-type groups*. Bull. Sci. Math. **137** (2013), no. 6, 805–833

K. FURUTANI: DEPARTMENT OF MATHEMATICS, FACULTY OF SCIENCE AND TECHNOLOGY, SCIENCE UNIVERSITY OF TOKYO, 2641 YAMAZAKI, NODA, CHIBA (278-8510), JAPAN

E-mail address: furutani_kenro@ma.noda.tus.ac.jp

I. MARKINA: DEPARTMENT OF MATHEMATICS, UNIVERSITY OF BERGEN, P.O. BOX 7803, BERGEN N-5020, NORWAY

E-mail address: irina.markina@uib.no